Dual and Quad 50MHz, 800V/µs Op Amps

FEATURES

- **50MHz Gain Bandwidth**
- **800V/µs Slew Rate**
- **5mA Maximum Supply Current per Amplifier**
- Unity-Gain Stable
- C-Load™ Op Amp Drives All Capacitive Loads
- 9nV/√Hz Input Noise Voltage
- 1mV Maximum Input Offset Voltage
- 1µA Maximum Input Bias Current
- 250nA Maximum Input Offset Current
- ±13V Minimum Output Swing into 500Ω
- ±3.2V Minimum Output Swing into 150Ω
- 4.5V/mV Minimum DC Gain, R_L=1k
- 60ns Settling Time to 0.1%, 10V Step
- 0.2% Differential Gain, A_V=2, R_L=150Ω
- 0.3° Differential Phase, A_V=2, R_L=150Ω
- Specified at ±2.5V, ±5V, and ±15V

APPLICATIONS

- Wideband Amplifiers
- Buffers
- Active Filters
- Video and RF Amplification
- Cable Drivers
- Data Acquisition Systems

DESCRIPTION

The LT1361/LT1362 are dual and quad low power high speed operational amplifiers with outstanding AC and DC performance. The amplifiers feature much lower supply current and higher slew rate than devices with comparable bandwidth. The circuit topology is a voltage feedback amplifier with matched high impedance inputs and the slewing performance of a current feedback amplifier. The high slew rate and single stage design provide excellent settling characteristics which make the circuit an ideal choice for data acquisition systems. Each output drives a 500Ω load to ±13V with ±15V supplies and a 150Ω load to ±3.2V on ±5V supplies. The amplifiers are stable with any capacitive load making them useful in buffer or cable driving applications.

The LT1361/LT1362 are members of a family of fast, high performance amplifiers using this unique topology and employing Linear Technology Corporation's advanced bipolar complementary processing. For a single amplifier version of the LT1361/LT1362 see the LT1360 data sheet. For higher bandwidth devices with higher supply currents see the LT1363 through LT1365 data sheets. For lower supply current amplifiers see the LT1354 to LT1359 data sheets. Singles, duals, and quads of each amplifier are available.

LT, LTC and LT are registered trademarks of Linear Technology Corporation.
C-Load is a trademark of Linear Technology Corporation

TYPICAL APPLICATION

Cable Driver Frequency Response



1361/1362 TA01

A_V = –1 Large-Signal Response



1361/1362 TA02

sales@prom-elec.com / ООО ПРОМЭЛЕКТРОНИКА

ABSOLUTE MAXIMUM RATINGS (Note 1)

Total Supply Voltage (V^+ to V^-) 36V
Differential Input Voltage
(Transient Only) (Note 2) ..... ±10V
Input Voltage ..... $\pm V_S$
Output Short-Circuit Duration (Note 3) ..... Indefinite

Operating Temperature Range (Note 8) ...–40°C to 85°C
Specified Temperature Range (Note 9) ....–40°C to 85°C
Maximum Junction Temperature (See Below)
Plastic Package ..... 150°C
Storage Temperature Range .....–65°C to 150°C
Lead Temperature (Soldering, 10 sec) ..... 300°C

PACKAGE/ORDER INFORMATION



N8 PACKAGE
8-LEAD PDIP

T_{JMAX} = 150°C, θ_{JA} = 130°C/W

ORDER PART NUMBER
LT1361CN8



S8 PACKAGE
8-LEAD PLASTIC SO

T_{JMAX} = 150°C, θ_{JA} = 190°C/W

ORDER PART NUMBER
LT1361CS8
S8 PART MARKING
1361



N PACKAGE
14-LEAD PDIP

T_{JMAX} = 150°C, θ_{JA} = 110°C/W

ORDER PART NUMBER
LT1362CN



S PACKAGE
16-LEAD PLASTIC SO

T_{JMAX} = 150°C, θ_{JA} = 150°C/W

ORDER PART NUMBER
LT1362CS

Consult factory for Industrial and Military grade parts.

ELECTRICAL CHARACTERISTICS T_A = 25°C, V_{CM} = 0V unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS	V_{SUPPLY}	MIN	TYP	MAX	UNITS
V_{OS}	Input Offset Voltage	(Note 4)	±15V ±5V ±2.5V		0.3 0.3 0.4	1.0 1.0 1.2	mV mV mV
I_{OS}	Input Offset Current		±2.5V to ±15V		80	250	nA
I_B	Input Bias Current		±2.5V to ±15V		0.3	1.0	µA
e_n	Input Noise Voltage	f = 10kHz	±2.5V to ±15V		9		$nV/\sqrt{Hz}$
i_n	Input Noise Current	f = 10kHz	±2.5V to ±15V		0.9		$pA/\sqrt{Hz}$
R_{IN}	Input Resistance	V_{CM} = ±12V	±15V	20	50		MΩ
	Input Resistance	Differential	±15V		5		MΩ
C_{IN}	Input Capacitance		±15V		3		pF

ELECTRICAL CHARACTERISTICS $T_A = 25°C$, $V_{CM} = 0V$ unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS	V_{SUPPLY}	MIN	TYP	MAX	UNITS
	Input Voltage Range +		±15V	12.0	13.4		V
			±5V	2.5	3.4		V
			±2.5V	0.5	1.1		V
	Input Voltage Range −		±15V		−13.2	−12.0	V
			±5V		−3.2	−2.5	V
			±2.5V		−0.9	−0.5	V
CMRR	Common Mode Rejection Ratio	V_{CM} = ±12V	±15V	86	92		dB
		V_{CM} = ±2.5V	±5V	79	84		dB
		V_{CM} = ±0.5V	±2.5V	68	74		dB
PSRR	Power Supply Rejection Ratio	V_S = ±2.5V to ±15V		93	105		dB
A_{VOL}	Large-Signal Voltage Gain	V_{OUT} = ±12V, R_L = 1k	±15V	4.5	9.0		V/mV
		V_{OUT} = ±10V, R_L = 500Ω	±15V	3.0	6.5		V/mV
		V_{OUT} = ±2.5V, R_L = 500Ω	±5V	3.0	6.4		V/mV
		V_{OUT} = ±2.5V, R_L = 150Ω	±5V	1.5	4.2		V/mV
		V_{OUT} = ±1V, R_L = 500Ω	±2.5V	2.5	5.2		V/mV
V_{OUT}	Output Swing	R_L = 1k, V_{IN} = ±40mV	±15V	13.5	13.9		±V
		R_L = 500Ω, V_{IN} = ±40mV	±15V	13.0	13.6		±V
		R_L = 500Ω, V_{IN} = ±40mV	±5V	3.5	4.0		±V
		R_L = 150Ω, V_{IN} = ±40mV	±5V	3.2	3.8		±V
		R_L = 500Ω, V_{IN} = ±40mV	±2.5V	1.3	1.7		±V
I_{OUT}	Output Current	V_{OUT} = ±13V	±15V	26	34		mA
		V_{OUT} = ±3.2V	±5V	21	29		mA
I_{SC}	Short-Circuit Current	V_{OUT} = 0V, V_{IN} = ±3V	±15V	40	54		mA
SR	Slew Rate	A_V = −2, (Note 5)	±15V	600	800		V/µs
			±5V	250	350		V/µs
	Full Power Bandwidth	10V Peak, (Note 6)	±15V		12.7		MHz
		3V Peak, (Note 6)	±5V		18.6		MHz
GBW	Gain Bandwidth	f = 200kHz	±15V	35	50		MHz
			±5V	25	37		MHz
			±2.5V		32		MHz
t_r, t_f	Rise Time, Fall Time	A_V = 1, 10%-90%, 0.1V	±15V		3.1		ns
			±5V		4.3		ns
	Overshoot	A_V = 1, 0.1V	±15V		35		%
			±5V		27		%
	Propagation Delay	50% V_{IN} to 50% V_{OUT}, 0.1V	±15V		5.2		ns
			±5V		6.4		ns
t_s	Settling Time	10V Step, 0.1%, A_V = −1	±15V		60		ns
		10V Step, 0.01%, A_V = −1	±15V		90		ns
		5V Step, 0.1%, A_V = −1	±5V		65		ns
	Differential Gain	f = 3.58MHz, A_V = 2, R_L = 150Ω	±15V		0.20		%
			±5V		0.20		%
		f = 3.58MHz, A_V = 2, R_L = 1k	±15V		0.04		%
			±5V		0.02		%
	Differential Phase	f = 3.58MHz, A_V = 2, R_L = 150Ω	±15V		0.40		Deg
			±5V		0.30		Deg
		f = 3.58MHz, A_V = 2, R_L = 1k	±15V		0.07		Deg
			±5V		0.26		Deg
R_O	Output Resistance	A_V = 1, f = 1MHz	±15V		1.4		Ω
	Channel Separation	V_{OUT} = ±10V, R_L = 500Ω	±15V	100	113		dB
I_S	Supply Current	Each Amplifier	±15V		4.0	5.0	mA
		Each Amplifier	±5V		3.8	4.8	mA

ELECTRICAL CHARACTERISTICS

The ● denotes the specifications which apply over the temperature range $0°C \le T_A \le 70°C$, V_{CM} = 0V unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS	V_{SUPPLY}		MIN	TYP	MAX	UNITS
V_{OS}	Input Offset Voltage	(Note 4)	±15V	●			1.5	mV
			±5V	●			1.5	mV
			±2.5V	●			1.7	mV
	Input V_{OS} Drift	(Note 7)	±2.5V to ±15V	●		9	12	µV/°C
I_{OS}	Input Offset Current		±2.5V to ±15V	●			350	nA
I_B	Input Bias Current		±2.5V to ±15V	●			1.5	µA
CMRR	Common Mode Rejection Ratio	V_{CM} = ±12V	±15V	●	84			dB
		V_{CM} = ±2.5V	±5V	●	77			dB
		V_{CM} = ±0.5V	±2.5V	●	66			dB
PSRR	Power Supply Rejection Ratio	V_S = ±2.5V to ±15V		●	91			dB
A_{VOL}	Large-Signal Voltage Gain	V_{OUT} = ±12V, R_L = 1k	±15V	●	3.6			V/mV
		V_{OUT} = ±10V, R_L = 500Ω	±15V	●	2.4			V/mV
		V_{OUT} = ±2.5V, R_L = 500Ω	±5V	●	2.4			V/mV
		V_{OUT} = ±2.5V, R_L = 150Ω	±5V	●	1.0			V/mV
		V_{OUT} = ±1V, R_L = 500Ω	±2.5V	●	2.0			V/mV
V_{OUT}	Output Swing	R_L = 1k, V_{IN} = ±40mV	±15V	●	13.4			±V
		R_L = 500Ω, V_{IN} = ±40mV	±15V	●	12.8			±V
		R_L = 500Ω, V_{IN} = ±40mV	±5V	●	3.4			±V
		R_L = 150Ω, V_{IN} = ±40mV	±5V	●	3.1			±V
		R_L = 500Ω, V_{IN} = ±40mV	±2.5V	●	1.2			±V
I_{OUT}	Output Current	V_{OUT} = ±12.8V	±15V	●	25			mA
		V_{OUT} = ±3.1V	±5V	●	20			mA
I_{SC}	Short-Circuit Current	V_{OUT} = 0V, V_{IN} = ±3V	±15V	●	32			mA
SR	Slew Rate	A_V = –2, (Note 5)	±15V	●	475			V/µs
			±5V	●	185			V/µs
GBW	Gain Bandwidth	f = 200kHz	±15V	●	31			MHz
			±5V	●	22			MHz
	Channel Separation	V_{OUT} = ±10V, R_L = 500Ω	±15V	●	98			dB
I_S	Supply Current	Each Amplifier	±15V	●			5.8	mA
		Each Amplifier	±5V	●			5.6	mA

The ● denotes the specifications which apply over the temperature range $-40°C \le T_A \le 85°C$, V_{CM} = 0V unless otherwise noted. (Note 9)

SYMBOL	PARAMETER	CONDITIONS	V_{SUPPLY}		MIN	TYP	MAX	UNITS
V_{OS}	Input Offset Voltage	(Note 4)	±15V	●			2.0	mV
			±5V	●			2.0	mV
			±2.5V	●			2.2	mV
	Input V_{OS} Drift	(Note 7)	±2.5V to ±15V	●		9	12	µV/°C
I_{OS}	Input Offset Current		±2.5V to ±15V	●			400	nA
I_B	Input Bias Current		±2.5V to ±15V	●			1.8	µA
CMRR	Common Mode Rejection Ratio	V_{CM} = ±12V	±15V	●	84			dB
		V_{CM} = ±2.5V	±5V	●	77			dB
		V_{CM} = ±0.5V	±2.5V	●	66			dB
PSRR	Power Supply Rejection Ratio	V_S = ±2.5V to ±15V		●	90			dB
A_{VOL}	Large-Signal Voltage Gain	V_{OUT} = ±12V, R_L = 1k	±15V	●	2.5			V/mV
		V_{OUT} = ±10V, R_L = 500Ω	±15V	●	1.5			V/mV
		V_{OUT} = ±2.5V, R_L = 500Ω	±5V	●	1.5			V/mV
		V_{OUT} = ±2.5V, R_L = 150Ω	±5V	●	0.6			V/mV
		V_{OUT} = ±1V, R_L = 500Ω	±2.5V	●	1.3			V/mV

ELECTRICAL CHARACTERISTICS

The ● denotes the specifications which apply over the temperature range $-40°C \le T_A \le 85°C$, V_{CM} = 0V unless otherwise noted. (Note 9)

SYMBOL	PARAMETER	CONDITIONS	V_{SUPPLY}		MIN	TYP	MAX	UNITS
V_{OUT}	Output Swing	R_L = 1k, V_{IN} = ±40mV	±15V	●	13.4			±V
		R_L = 500Ω, V_{IN} = ±40mV	±15V	●	12.0			±V
		R_L = 500Ω, V_{IN} = ±40mV	±5V	●	3.4			±V
		R_L = 150Ω, V_{IN} = ±40mV	±5V	●	3.0			±V
		R_L = 500Ω, V_{IN} = ±40mV	±2.5V	●	1.2			±V
I_{OUT}	Output Current	V_{OUT} = ±12.0V	±15V	●	24			mA
		V_{OUT} = ±3.0V	±5V	●	20			mA
I_{SC}	Short-Circuit Current	V_{OUT} = 0V, V_{IN} = ±3V	±15V	●	30			mA
SR	Slew Rate	A_V = –2, (Note 5)	±15V	●	450			V/µs
			±5V	●	175			V/µs
GBW	Gain Bandwidth	f = 200kHz	±15V	●	30			MHz
			±5V	●	20			MHz
	Channel Separation	V_{OUT} = ±10V, R_L = 500Ω	±15V	●	98			dB
I_S	Supply Current	Each Amplifier	±15V	●			6.0	mA
		Each Amplifier	±5V	●			5.8	mA

Note 1: Absolute Maximum Ratings are those values beyond which the life of a device may be impaired.

Note 2: Differential inputs of ±10V are appropriate for transient operation only, such as during slewing. Large, sustained differential inputs will cause excessive power dissipation and may damage the part. See Input Considerations in the Applications Information section of this data sheet for more details.

Note 3: A heat sink may be required to keep the junction temperature below absolute maximum when the output is shorted indefinitely.

Note 4: Input offset voltage is pulse tested and is exclusive of warm-up drift.

Note 5: Slew rate is measured between ±10V on the output with ±6V input for ±15V supplies and ±1V on the output with ±1.75V input for ±5V supplies.

Note 6: Full power bandwidth is calculated from the slew rate measurement: $FPBW = SR/2\pi V_P$.

Note 7: This parameter is not 100% tested.

Note 8: The LT1361C/LT1362C are guaranteed functional over the operating temperature range of –40°C to 85°C.

Note 9: The LT1361C/LT1362C are guaranteed to meet specified performance from 0°C to 70°C. The LT1361C/LT1362C are designed, characterized and expected to meet specified performance from –40°C to 85°C, but are not tested or QA sampled at these temperatures. For guaranteed I-grade parts, consult the factory.

TYPICAL PERFORMANCE CHARACTERISTICS

Supply Current vs Supply Voltage and Temperature



Input Common Mode Range vs Supply Voltage



Input Bias Current vs Input Common Mode Voltage



TYPICAL PERFORMANCE CHARACTERISTICS

Input Bias Current vs Temperature



Input Noise Spectral Density



Open-Loop Gain vs Resistive Load



Open-Loop Gain vs Temperature



Output Voltage Swing vs Supply Voltage



Output Voltage Swing vs Load Current



Output Short-Circuit Current vs Temperature



Settling Time vs Output Step (Noninverting)



Settling Time vs Output Step (Inverting)



TYPICAL PERFORMANCE CHARACTERISTICS

Output Impedance vs Frequency



1361/1362 G13

Gain and Phase vs Frequency



1361/1362 G14

Crosstalk vs Frequency



1361/1362 G21

Gain Bandwidth and Phase Margin vs Temperature



1361/1362 G16

Frequency Response vs Supply Voltage (A_V = 1)



1361/1362 G17

Frequency Response vs Capacitive Load



1361/1362 G18

Gain Bandwidth and Phase Margin vs Supply Voltage



1361/1362 G15

Power Supply Rejection Ratio vs Frequency



1361/1362 G19

Common Mode Rejection Ratio vs Frequency



1361/1362 G20

TYPICAL PERFORMANCE CHARACTERISTICS

Slew Rate vs Supply Voltage



1361/1362 G22

Slew Rate vs Temperature



1361/1362 G23

Slew Rate vs Input Level



1361/1362 G24

Total Harmonic Distortion vs Frequency



1361/1362 G25

Undistorted Output Swing vs Frequency (±15V)



1361/1362 G26

Undistorted Output Swing vs Frequency (±5V)



1361/1362 G27

2nd and 3rd Harmonic Distortion vs Frequency



1361/1362 G28

Differential Gain and Phase vs Supply Voltage



1361/1362 G29

Capacitive Load Handling



1361/1362 G30

TYPICAL PERFORMANCE CHARACTERISTICS

Small-Signal Transient (A_V = 1)



1361/1362 TA31

Small-Signal Transient (A_V = –1)



1361/1362 TA32

Small-Signal Transient (A_V = –1, C_L = 500pF)



1361/1362 TA33

Large-Signal Transient (A_V = 1)



1361/1362 TA34

Large-Signal Transient (A_V = –1)



1361/1362 TA35

Large-Signal Transient (A_V = 1, C_L = 10,000pF)



1361/1362 TA36

APPLICATIONS INFORMATION

Layout and Passive Components

The LT1361/LT1362 amplifiers are easy to use and tolerant of less than ideal layouts. For maximum performance (for example, fast 0.01% settling) use a ground plane, short lead lengths, and RF-quality bypass capacitors (0.01μF to 0.1μF). For high drive current applications use low ESR bypass capacitors (1μF to 10μF tantalum). The parallel combination of the feedback resistor and gain setting resistor on the inverting input combine with the input capacitance to form a pole which can cause peaking or oscillations. If feedback resistors greater than 5kΩ are used, a parallel capacitor of value

$$C_F > R_G \times C_{IN}/R_F$$

should be used to cancel the input pole and optimize dynamic performance. For unity-gain applications where a large feedback resistor is used, C_F should be greater than or equal to C_{IN}.

Input Considerations

Each of the LT1361/LT1362 inputs is the base of an NPN and a PNP transistor whose base currents are of opposite polarity and provide first-order bias current cancellation. Because of variation in the matching of NPN and PNP beta, the polarity of the input bias current can be positive or negative. The offset current does not depend on NPN/PNP beta matching and is well controlled. The use of balanced source resistance at each input is recommended for applications where DC accuracy must be maximized.

The inputs can withstand transient differential input voltages up to 10V without damage and need no clamping or source resistance for protection. Differential inputs, however, generate large supply currents (tens of mA) as required for high slew rates. If the device is used with sustained differential inputs, the average supply current will increase, excessive power dissipation will result and the part may be damaged. **The part should not be used as a comparator, peak detector or other open-loop applica-**

APPLICATIONS INFORMATION

tion with large, sustained differential inputs. Under normal, closed-loop operation, an increase of power dissipation is only noticeable in applications with large slewing outputs and is proportional to the magnitude of the differential input voltage and the percent of the time that the inputs are apart. Measure the average supply current for the application in order to calculate the power dissipation.

Capacitive Loading

The LT1361/LT1362 are stable with any capacitive load. This is accomplished by sensing the load induced output pole and adding compensation at the amplifier gain node. As the capacitive load increases, both the bandwidth and phase margin decrease so there will be peaking in the frequency domain and in the transient response as shown in the typical performance curves. The photo of the small signal response with 500pF load shows 60% peaking. The large signal response shows the output slew rate being limited to 5V/µs by the short-circuit current. Coaxial cable can be driven directly, but for best pulse fidelity a resistor of value equal to the characteristic impedance of the cable (i.e., 75Ω) should be placed in series with the output. The other end of the cable should be terminated with the same value resistor to ground.

Circuit Operation

The LT1361/LT1362 circuit topology is a true voltage feedback amplifier that has the slewing behavior of a current feedback amplifier. The operation of the circuit can be understood by referring to the simplified schematic. The inputs are buffered by complementary NPN and PNP emitter followers which drive a 500Ω resistor. The input voltage appears across the resistor generating currents which are mirrored into the high impedance node. Complementary followers form an output stage which buffers the gain node from the load. The bandwidth is set by the input resistor and the capacitance on the high impedance node. The slew rate is determined by the current available to charge the gain node capacitance. This current is the differential input voltage divided by R1, so the slew rate is proportional to the input. Highest slew rates are therefore seen in the lowest gain configurations. For example, a 10V output step in a gain of 10 has only a 1V input step, whereas the same output step in unity gain has a 10 times greater input step. The curve of Slew Rate vs Input Level illustrates this relationship. The LT1361/LT1362 are tested for slew rate in a gain of –2 so higher slew rates can be expected in gains of 1 and –1, and lower slew rates in higher gain configurations.

The RC network across the output stage is bootstrapped when the amplifier is driving a light or moderate load and has no effect under normal operation. When driving a capacitive load (or a low value resistive load) the network is incompletely bootstrapped and adds to the compensation at the high impedance node. The added capacitance slows down the amplifier which improves the phase margin by moving the unity-gain frequency away from the pole formed by the output impedance and the capacitive load. The zero created by the RC combination adds phase to ensure that even for very large load capacitances, the total phase lag can never exceed 180 degrees (zero phase margin) and the amplifier remains stable.

Power Dissipation

The LT1361/LT1362 combine high speed and large output drive in small packages. Because of the wide supply voltage range, it is possible to exceed the maximum junction temperature under certain conditions. Maximum junction temperature (T_J) is calculated from the ambient temperature (T_A) and power dissipation (P_D) as follows:

LT1361CN8: $T_J = T_A + (P_D \times 130°C/W)$
LT1361CS8: $T_J = T_A + (P_D \times 190°C/W)$
LT1362CN: $T_J = T_A + (P_D \times 110°C/W)$
LT1362CS: $T_J = T_A + (P_D \times 150°C/W)$

Worst case power dissipation occurs at the maximum supply current and when the output voltage is at 1/2 of either supply voltage (or the maximum swing if less than 1/2 supply voltage). For each amplifier P_{DMAX} is:

$$P_{DMAX} = (V^+ - V^-)(I_{SMAX}) + (V^+/2)^2/R_L$$

Example: LT1362 in S16 at 70°C, $V_S = \pm 5V$, $R_L = 100\Omega$

$$P_{DMAX} = (10V)(5.6mA) + (2.5V)^2/100\Omega = 119mW$$

$$T_{JMAX} = 70°C + (4 \times 119mW)(150°C/W) = 141°C$$

SIMPLIFIED SCHEMATIC



PACKAGE DESCRIPTION

Dimension in inches (millimeters) unless otherwise noted.

N8 Package
8-Lead PDIP (Narrow 0.300)
(LTC DWG # 05-08-1510)



*THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS.
MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED 0.010 INCH (0.254mm)

N Package
14-Lead PDIP (Narrow 0.300)
(LTC DWG # 05-08-1510)



*THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS.
MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED 0.010 INCH (0.254mm)

Information furnished by Linear Technology Corporation is believed to be accurate and reliable. However, no responsibility is assumed for its use. Linear Technology Corporation makes no representation that the interconnection of its circuits as described herein will not infringe on existing patent rights.

TYPICAL APPLICATIONS

Two Op Amp Instrumentation Amplifier



$$\text{GAIN} = \left[\frac{R4}{R3}\right]\left[1+\left(\frac{1}{2}\right)\left(\frac{R2}{R1}+\frac{R3}{R4}\right)+\frac{(R2+R3)}{R5}\right]=102$$

TRIM R5 FOR GAIN
TRIM R1 FOR COMMON-MODE REJECTION
BW = 500kHz

1MHz, 4th Order Butterworth Filter



PACKAGE DESCRIPTION

Dimension in inches (millimeters) unless otherwise noted.

S8 Package
8-Lead Plastic Small Outline (Narrow 0.150)
(LTC DWG # 05-08-1610)



*DIMENSION DOES NOT INCLUDE MOLD FLASH. MOLD FLASH SHALL NOT EXCEED 0.006" (0.152mm) PER SIDE
**DIMENSION DOES NOT INCLUDE INTERLEAD FLASH. INTERLEAD FLASH SHALL NOT EXCEED 0.010" (0.254mm) PER SIDE

S Package
16-Lead Plastic Small Outline (Narrow 0.150)
(LTC DWG # 05-08-1610)



*DIMENSION DOES NOT INCLUDE MOLD FLASH. MOLD FLASH SHALL NOT EXCEED 0.006" (0.152mm) PER SIDE
**DIMENSION DOES NOT INCLUDE INTERLEAD FLASH. INTERLEAD FLASH SHALL NOT EXCEED 0.010" (0.254mm) PER SIDE

RELATED PARTS

PART NUMBER	DESCRIPTION	COMMENTS
LT1360	50MHz, 800V/µs Op Amp	Single Version of LT1361/LT1362
LT1364/LT1365	Dual and Quad 70MHz, 1000V/µs Op Amps	Faster Version of LT1361/LT1362, V_{OS} = 1.5mV, I_S = 6.3mA/Amplifier
LT1358/LT1359	Dual and Quad 25MHz, 600Vµs Op Amps	Lower Power Version of LT1361/LT1362, V_{OS} = 0.6mV, I_S = 2mA/Amplifier
LT1813	Dual 100MHz, 700V/µs Op Amps	Low Voltage, Low Power LT1361, I_S = 3mA/Amplifier

Linear Technology Corporation
1630 McCarthy Blvd., Milpitas, CA 95035-7417
(408)432-1900 • FAX: (408) 434-0507 • www.linear-tech.com
13612fa LT/TP 0400 2K REV A • PRINTED IN USA
© LINEAR TECHNOLOGY CORPORATION 1994