Draco 4G Terminal Antenna

Part No. SREL036 External Antenna Product Specification

1. Features

- Terminal antenna for 4G/3G/2G applications
- LTE, HSPA+, WCDMA, CDMA, GSM, GPRS, DCS1800, PCS1900
- LTE bands: 1-21; 23-30; 33-41
- 698-960MHz, 1427-1660MHz, 1710-2170MHz, 2300-2400MHz, 2500-2690MHz
- High performance dipole design
- Available in three terminal options: swivel, fly lead and fixed 90° (IPC68)

2. Description

Draco is constructed with an ergonomic blade design to blend well to the outside of a device. Three versions are available, including an IPC68 design for outdoor applications. The antenna is designed to work to various GND plane sizes or in free space for ease of integration.

3. Applications

- Routers
- Industrial devices
- Remote devices
- ISM









Antennas for Wireless M2M Applications

ПРОМЭЛЕКТРОНИКА/ sales@prom-elec.com

4. Part Number

Note. -xxx refers to options for antenna version, connector type and cable length:

Draco: SREL036-XXX

-XX X

Antenna Type	xx
IP68 version	IP
Swivel version	S9

Cable Length (If fly Lead)	xx
1.0 m	10
1.5 m	15
1.7 m	17
2.0 m	20

x	Connector
P	SMA Plug

*Non-Standard connectors**

x	
R	SMA Plug Reverse
J	SMA Jack
K	SMA Jack Reverse

**Please contact Antenova for details on non-standard connector types*

5. General Data

Product name	Draco
Part Number	SREL036-xxx
Frequency	698-960 MHz 1427-1660MHz 1720-2170MHz 2300-2400MHz 2500-2690MHz
Polarization	Linear
Operating temperature	-20°C to +70°C
Impedance with matching	50 Ω
Weight	< 21g (Cable not included)
Dimensions (Antenna)	See dimensions from page 18>
Cable length (Fly lead only)	1.0m /2.0m *
Connection	SMA Plug (Standard)
Radome Material	PC

**Please contact Antenova for details on other cable lengths*

6. RF Characteristics

The RF characteristics are shown for each type.

	698 – 960 MHz		
	Fixed (IPC68)	Hinged	Fly Lead (1.0m)
			
Peak gain	2.46dBi	2.18dBi	1.23dBi
Average gain	-2.26dBi	-2.32dBi	-3.10dBi
Average efficiency	>55%	>56%	>45%
Maximum return loss	<-5.30dB	<-5.56dB	<-6.65dB
Maximum VSWR	3.30:1	3.25 :1	2.60:1

	1420 – 1660 MHz		
	Fixed (IPC68)	Hinged	Fly Lead (1.0m)
Peak gain	2.07dBi	1.92dBi	1.23dBi
Average gain	-2.63dBi	-2.59dBi	-3.38dBi
Average efficiency	>53%	>55%	>48%
Maximum return loss	<-7.50dB	<-7.50dB	<-14.90dB
Maximum VSWR	2.40:1	2.40:1	1.40:1

	1720 – 2170 MHz		
	Fixed (IPC68)	Hinged	Fly Lead (1.0m)
Peak gain	3.33dBi	3.29dBi	1.73dBi
Average gain	-2.33dBi	-2.35dBi	-3.33dBi
Average efficiency	>57%	>57%	>46%
Maximum return loss	<-7.80dB	<-7.60dB	<-10.10dB
Maximum VSWR	2.30:1	2.40:1	1.90:1

	2300 – 2400 MHz		
	Fixed (IPC68)	Hinged	Fly Lead (1.0m)
Peak gain	3.29dBi	3.23dBi	1.51dBi
Average gain	-1.81dBi	-2.12dBi	-3.17dBi
Average efficiency	>65%	>60%	>48%
Maximum return loss	<-8.90dB	<-9.40dB	<-14.11dB
Maximum VSWR	2.10:1	2.00:1	1.50:1

	2500 – 2690 MHz		
	Fixed (IPC68)	Hinged	Fly Lead (1.0m)
Peak gain	4.14dBi	4.08dBi	1.59dBi
Average gain	-1.84dBi	-2.17dBi	-3.11dBi
Average efficiency	>65%	>60%	>48%
Maximum return loss	<-7.40dB	<-5.50dB	<-10.30dB
Maximum VSWR	2.50:1	3.20:1	1.90:1

7. RF Performance

7.1 Return Loss



MARKERS:	MHz	dB	MHz	dB	MHz	dB	MHz	dB	MHz	dB
Fixed.S1P - S11										
	1: 698	-8.96	3: 1427	-11.07	5: 1710	-18.97	7: 2300	-8.91	9: 2500	-21.64
	2: 960	-6.13	4: 1661	-19.98	6: 2170	-9.91	8: 2400	-12.54	10: 2690	-7.47
Hinged.S1P - S11										
	1: 698	-7.73	3: 1427	-7.59	5: 1710	-13.95	7: 2300	-9.49	9: 2500	-19.66
	2: 960	-9.00	4: 1661	-17.19	6: 2170	-8.57	8: 2400	-12.23	10: 2690	-5.55
Flylead.S1P - S11										
	1: 698	-8.58	3: 1427	-20.09	5: 1710	-18.88	7: 2300	-14.11	9: 2500	-15.68
	2: 960	-6.55	4: 1661	-17.55	6: 2170	-12.41	8: 2400	-22.48	10: 2690	-10.38

7.2 VSWR



MARKERS:	MHz		MHz		MHz		MHz		MHz	
Fixed.S1P - S11										
	1: 698	2.11	3: 1427	1.78	5: 1710	1.25	7: 2300	2.12	9: 2500	1.18
	2: 960	2.95	4: 1661	1.22	6: 2170	1.94	8: 2400	1.62	10: 2690	2.47
Hinged.S1P - S11										
	1: 698	2.39	3: 1427	2.43	5: 1710	1.50	7: 2300	2.01	9: 2500	1.23
	2: 960	2.10	4: 1661	1.32	6: 2170	2.19	8: 2400	1.65	10: 2690	3.24
Flylead.S1P - S11										
	1: 698	2.19	3: 1427	1.22	5: 1710	1.26	7: 2300	1.49	9: 2500	1.39
	2: 960	2.78	4: 1661	1.31	6: 2170	1.63	8: 2400	1.16	10: 2690	1.87

7.3 Antenna Pattern Free Space

7.3.1 698 MHz – 960 MHz

Fixed (IPC68)



XY XZ YZ



Hinged



XY XZ YZ



Fly Lead (1.0m)



XY XZ YZ



7.3.2 1427 MHz – 1661 MHz

Fixed (IPC68)



XY XZ YZ



Hinged



XY XZ YZ



Fly Lead (1.0m)



XY XZ YZ



7.3.3 1710 MHz – 2170 MHz

Fixed (IPC68)



XY



XZ



YZ



Hinged



XY



XZ



YZ



Fly Lead (1.0m)



XY



XZ



YZ



7.3.4 2300 MHz – 2400 MHz

Fixed (IPC68)



XY



XZ



YZ



Hinged



XY



XZ



YZ



Fly Lead (1.0m)



XY



XZ



YZ



7.3.5 2500 MHz – 2690 MHz

Fixed (IPC68)



XY



XZ



YZ



Hinged



XY



XZ



YZ



Fly Lead (1.0m)



XY



XZ



YZ



7.4 Antenna Pattern Free Space (3D)

7.4.1 698 MHz – 960 MHz

3D patterns at 746MHz

Drag to rotate pattern and PCB by using Adobe Reader
(Click to Activate)

Fixed (IPC68)



Hinged



Fly Lead (1.0m)



7.4.2 1427 MHz – 1661 MHz

3D patterns at 1500MHz

Drag to rotate pattern and PCB by using Adobe Reader
(Click to Activate)

Fixed (IPC68)



Hinged



Fly Lead (1.0m)



7.4.3 1710 MHz – 2170 MHz

3D patterns at 1930MHz

Drag to rotate pattern and PCB by using Adobe Reader
(Click to Activate)

Fixed (IPC68)



Hinged



Fly Lead (1.0m)



7.4.4 2300 MHz – 2400 MHz

3D patterns at 2350MHz

Drag to rotate pattern and PCB by using Adobe Reader
(Click to Activate)

Fixed (IPC68)



Hinged



Fly Lead (1.0m)



7.4.5 2500 MHz – 2690 MHz

3D patterns at 2600MHz

Drag to rotate pattern and PCB by using Adobe Reader
(Click to Activate)

Fixed (IPC68)



Hinged



Fly Lead (1.0m)



8. Antenna Dimensions

8.1 Dimensions Fixed (SREL036-IPP)



All dimensions in mm

8.1 Dimensions Hinged (SREL036-S9P)



All dimensions in mm

8.1 Dimensions Fly lead (SREL036-10P)



All dimensions in mm

9. Electrical Interface

9.1 Transmission Line

All transmission lines should be designed to have a characteristic impedance of 50Ω.

• The length of the transmission lines should be kept to a minimum
• Any other parts of the RF system like transceivers, power amplifiers, etc, should also be designed to have an impedance of 50 Ω

Once the material for the PCB has been chosen (PCB thickness and dielectric constant), a coplanar transmission line can easily be designed using any of the commercial software packages for transmission line design. For the chosen PCB thickness, copper thickness and substrate dielectric constant, the program will calculate the appropriate transmission line width and gaps on either side of the feed.

A DC blocking capacitor should be placed in line to protect the RF front end.

10. Hazardous Material Regulation Conformance

The antenna has been tested to conform to RoHS requirements. A certificate of conformance is available from Antenova M2M's website.

11. Packaging

11.1 Fixed (SREL036-IPP)



The antennas are supplied in individual polythene bags. Twenty five small bags are packed in one larger bag. The outer box contains fifty antennas.

Box label



Width W	Breadth B	Thickness H
355 mm	340 mm	58 mm

11.2 Hinged (SREL036-S9P)



The antennas are supplied in individual polythene bags. Twenty five small bags are packed in one larger bag. The outer box contains fifty antennas.

Box label



Width W	Breadth B	Thickness H
355 mm	340 mm	58 mm

11.3 Fly lead (SREL036-10P)



The antennas are supplied in individual polythene bags. Twenty five small bags are packed in one larger bag. The outer box contains fifty antennas.

Box label



Width W	Breadth B	Thickness H
355 mm	340 mm	58 mm

12. Optimal Storage Conditions

Temperature	-10ºC to 40ºC
Humidity	Less than 75% RH
Shelf life	18 Months
Storage place	Away from corrosive gas and direct sunlight
Packaging	Antennas should be stored in unopened sealed manufacturer's plastic packaging.

13. Label Information



www.antenova-m2m.com

Corporate Headquarters

Antenova Limited
2nd Floor Titan Court
3 Bishop Square
Hatfield
AL10 9NA
UK

Tel: +44 1223 810600
Email: sales@antenova-m2m.com

North America Headquarters

Antenova Limited
100 Brush Creek Road
Suite 103, Santa Rosa
California 95404
USA

Tel: +1 707 890 5202
Email: sales@antenova-m2m.com

Asia Headquarters

Antenova Asia Limited
4F, No. 324, Sec. 1, Nei-Hu Road
Nei-Hu District
Taipei 11493
Taiwan, ROC

Tel: +886 (0) 2 8797 8630
Fax: +886 (0) 2 8797 6890
Email: sales@antenova-m2m.com

Copyright® Antenova Ltd. All Rights Reserved. Antenova ®, Antenova M2M ®, gigaNOVA ®, the Antenova product family names and the Antenova and Antenova M2M logos are trademarks and/or registered trademarks of Antenova Ltd. Any other names and/or trademarks belong to their respective companies.

The materials provided herein are believed to be reliable and correct at the time of printing. Antenova does not warrant the accuracy or completeness of the information, text, graphics or other items contained within this information. Antenova further assumes no responsibility for the use of this information, and all such information shall be entirely at the user's risk.

ISOQAR REGISTERED
UKAS MANAGEMENT SYSTEMS 0026
Certificate No. 11070
ISO 9001